



**UL Product iQ**  
**UL'S NEXT GENERATION CERTIFICATIONS SEARCH**  
 The same trusted data in a modern search engine.

**NOW AVAILABLE**

**▶ LEARN MORE**

XCFR2.E80027  
 Terminal Blocks - Component

[Page Bottom](#)

Terminal Blocks - Component

[See General Information for Terminal Blocks - Component](#)

SIEMENS AG  
 LOW VOLTAGE  
 SIEMENSSTRASSE 10  
 93055 REGENSBURG, GERMANY

E80027

Cat. No.	Wire Range	Wire Type	FW	TQ Lb In.	V	A	UG	CA
8WA1-232	—	—	1	—	600	24	C	2(105),*
8WA1-817	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-818	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-1BF21	22-12	Cu	2	—	600	20	C	2(105),*
8WA1-011-1BF22	22-12	Cu	2	6	600	20	C	2(105),*
8WA1-011-1BF23	22-12	Cu	2	6	600	20	C	2(105),*
8WA1-011-3DF21	22-12	Cu	2	6	600	20	C	2(105),*
8WA1-011-ODF21	22-12	Cu	2	6	600	20	C	2(105),*
8WA1-011-ODF22	22-12	Cu	2	6	600	20	C	2(105),*
8WA1-011-1NF01	22-12	Cu	2	6	600	20	C	2(105),*
8WA1-011-1NF02	22-12	Cu	2	6	600	20	C	2(105),*
8WA1-011-1BG11	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-1BG21	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-1BG22	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-1NG31	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-1NG32	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-1BH23	14-8(1)	Cu	2	8	600	44	C	2(105),*
8WA1-011-1DF11	22-12	Cu	2	6	600	20	C	2(105),*
8WA1-011-1DG11	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-1DH11	14-8(3)	Cu	2	8	600	44	C	2(105),*
8WA1-011-1MH10	14-8(3)	Cu	2	8	600	44	C	2(105),*
8WA1-011-1MH11	14-8(3)	Cu	2	8	600	44	C	2(105),*
8WA1-011-1MH15	14-8(3)	Cu	2	8	600	44	C	2(105),*
8WA1011-1NH01	14-8(3)	Cu	2	8	600	44	C	2(105),*
8WA1011-1NH02	14-8(3)	Cu	2	8	600	44	C	2(105),*
8WA1-011-3DH21	14-8(3)	Cu	2	8	600	44	C	2(105),*
8WA1-011-1PF11	22-12	Cu	2	6	—	—	C	2(105),*
8WA1-011-1BF26	22-12	Cu	2	6	—	—	C	2(105),*
8WA1-011-1PH11	14-8(3)	Cu	2	8	—	—	C	2(105),*
8WA1-011-1SF12	18-14	Cu	2	6	600	7	C	2(120),#10
8WA1-011-1SF13, 8WA1-011-1SF14, 8WA1-011-1SF15	18-14	Cu	2	7	600	6.3	C	2(120),#10

8WA1-011-1SF30, 8WA1-011-1SF31, 8WA1-011-1SF32	18-14	Cu	2	7	600	6.3	C	2(120),#10
8WA-011-1PK00	12-4	Cu	2	12	—	—	B,C	2(105),*
8WA1-011(1)	22-12	Cu	2	8	300	34	B,C	2(105),*
8WA1-011(2)	22-12	Cu	2	6	300	26	B,C	2(105),*
8WA1-011-1PG11	18-10	Cu	2	8	—	—	C	2(105),*
8WA1-011-1BG24	18-10	Cu	2	8	600	30	C	2(105),4
	18-10	Cu	1	8	600	35	C	2(105),*
8WA1-011-1BH24	14-8(3)	Cu	2	8	600	44	C	2(105),4
Note: (1) Followed by -6EG , followed by 20 thru 27 incl. 44, 51.								
Note: (2) Followed by -3JF, followed by 10, 12 thru 18 incl., and 20.								
Note: (3) Multiple wire combinations for field and factory-wiring of 2 No. 14-10 AWG Cu. sol/str (same size wires, str. and sol. not intermixed), and 1 No. 8 AWG Cu. str. with 1 No. 14 AWG Cu str. wire.								
8WA1-011-2BG11	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-2DG11	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-6BG11	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-6DG11	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-3DG21	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-ODG21	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-ODG22	18-10	Cu	2	8	600	30	C	2(105),*
8WA1-011-1BK11	8-4str,	Cu	2	18	600	79	C	2(105)
	12-10sol							
8WA1-204	8-4str,	Cu	2	18	600	79	C	2(105)
	12-10sol							
8WA1-304	8-4str,	Cu	2	18	600	79	C	2(105)
	12-10sol							
8WA1-011-1BM11	10-1	Cu	2	27	600	120	C	2(105)
8WA1-205	10-1	Cu	2	27	600	120	C	2(105)
8WA1-206	8-3/0	Cu	1	—	600	220	C	2(105)
8WA1-207	1/0-250	Cu	2	90	600	320	C	2(105),*
8WA1-208	2/0-500	Cu	2	140	600	380	C	2(105),*
8WA1-305	10-1	Cu	2	27	600	120	C	2(105)
8WA1011-1BP11	2/0	Cu	2	53	800	192	E	2(105),4
8WA9-200	18-10	Cu	1	8	600	26	B	2(105),*
8WA9-203	18-10	Cu	1	8	600	26	B	2(105),*
8WA1-011-1NG01	18-10	Cu	2	8	300	30	B,C	2(105),*
8WA1-011-1NG02	18-10	Cu	2	8	300	30	B,C	2(105),*
8WA1-011-1NK02	12-4	Cu	2	18	300	73	B,C	2(105),*
8WA1-604	12-4	Cu	2	18	300	73	B,C	2(105),*
8WA1-011-1PG00	18-10	Cu	2	8	—	—	B,C	2(105),*
8WA1-011-1PG01	18-10	Cu	2	8	—	—	B,C	2(105),*
8WA9-210	14	Cu	1	—	300	63	C	2(105),*
8WA1-011-1PF00	22-12	Cu	2	6	—	—	B,C	2(105),*
8WA1-011-1PF01	22-12	Cu	2	6	—	—	B,C	2(105),*
8WA1 011 1PF11	22-12	Cu	2	6	—	—	B,C	2(105),*
8WA1-011-1PH00	14-8	Cu	2	6	—	—	B,C	2(105),*
8WA1501	22-12	Cu	2	5.25	300	10	D	2(105),4
8WA1501xx	14 sol/str	Cu	2	4.4	380Vac/450Vdc	10	D	2(105),4
8WA2 011-3KE(1)	22-16	Cu	2	—	65	10	D	2(120),*
8WA1-011-1PM00	10-1	Cu	2	27	—	—	C	2(120)

(1) Followed by numbers 00, 01 , 02, 03, 10 thru 15, 22, 30, 31, 33, 35 , 50 or 51.								
8WA20111DF20	28-14	Cu	2	—	600	15	B,C	2(105),*
8WA20111BF21	28-14	Cu	2	—	600	15	B,C	2(105),*
8WA20111BF23	28-14	Cu	2	—	600	15	B,C	2(105),*
8WA20111BF33	28-14	Cu	2	—	600	15	B,C	2(105),*
8WA20111DF30	28-14	Cu	2	—	600	15	B,C	2(105),*
8WA20111DG20	28-12	Cu	2	—	600	20	B,C	2(105),*
8WA20111BG21	28-12	Cu	2	—	600	20	B,C	2(105),*
8WA20111BG23	28-12	Cu	2	—	600	20	B,C	2(105),*
8WA20111DG30	28-12	Cu	2	—	600	20	B,C	2(105),*
8WA20111BG33	28-12	Cu	2	—	600	20	B,C	2(105),*
8WA20111NG23	28-12	Cu	2	—	600	20	B,C	2(105),*
8WA20112BG23	28-12	Cu	2	N/A	600	20	B	2(120),*
8WA20112BG43	28-12	Cu	2	N/A	600	20	B	2(120),*
8WA20112DG20	28-12	Cu	2	N/A	600	20	B	2(120),*
8WA20112DG40	28-12	Cu	2	N/A	600	20	B	2(120),*
8WA20113JG10	28-12	Cu	2	N/A	300	20	B	2(120),*
8WA20113JG12	28-12	Cu	2	N/A	300	20	B	2(120),*
8WA20113JG15	28-12	Cu	2	N/A	300	20	B	2(120),*
8WA20113JG16	28-12	Cu	2	N/A	300	20	B	2(120),*
8WA20113JG17	28-12	Cu	2	N/A	300	20	B	2(120),*
8WA20113JG18	28-12	Cu	2	N/A	300	20	B	2(120),*
8WA20111DH20	24-10	Cu	2	—	300	30	B,C	2(105),*
8WA20111BH23	24-10	Cu	2	—	300	30	B,C	2(105),*
8WA20111NH23	24-10	Cu	2	—	300	30	B,C	2(105),*
8WA20111PF20, -30, -40	28-14	Cu	2	—	—	—	B,C	2(105),*
8WA20111PG20	28-12	Cu	2	—	—	—	B,C	2(105),*
8WA20111PG30	28-12	Cu	2	—	—	—	B,C	2(105),*
8WA20111PH20	24-10	Cu	2	—	—	—	B,C	2(105),*
8WA20111NK23	28-4	Cu	2	10.8	600	63	B,C	2(105),*
8WA20113JG11	12-4	Cu	2	10.8	600	63	B,C	2(105),*
8WA20111EF20	28-14	Cu	2	N/A	300	30	B,C	2(105),*
8WA20116EG20	28-12	Cu	2	N/A	300	30	B,C	2(105),*
8WA20116EG21	28-12	Cu	2	N/A	300	20(1)	B,C	2(105),*
8WA20116EG22	28-12	Cu	2	N/A	300	20(1)	B,C	2(105),*
8WA20116EG23	28-12	Cu	2	N/A	300	20(1)	B,C	2(105),*
8WA20116EG24	28-12	Cu	2	N/A	300	20(1)	B,C	2(105),*
8WA20116EG25	28-12	Cu	2	N/A	300	20(1)	B,C	2(105),*
8WA2 011-1BF43, 8WA2 011-1DF40, 8WA2 011-1LF20	28-14	Cu	2	N/A	600	10	B,C	2(105),4,#
8WA2 011-1SG20, 8WA2 011-1SG21, 8WA2 011-1SG22, -8WA2 011-1SG23, 8WA2 011-1SG28	28-12	Cu	2	N/A	600	6.3	B,C	2(105),4,#
8WA2 011-3JH10	24-10	Cu	2	N/A	600	30	B,C	2(105),4,#
8WA2 011-1BJ23, 8WA2 011-1DJ20	24-8	Cu	2	N/A	600	50	B,C	2(105),4,#
8WA2 011-1BK23, 8WA2 011-1DK20, 8WA2 011-1NK20	24-6	Cu	2	N/A	600	65	B,C	2(105),4,#
8WA2 011-1PF40	24-14	Cu	2	N/A	—	—	B,C	2(105),4,#
8WA2 011-1PJ20	24-8	Cu	2	N/A	—	—	B,C	2(105),4,#
8WA2 011-1PK20	24-6	Cu	2	N/A	—	—	B,C	2(105),4,#
8WA 2511-1DF20	26-12	Cu	2	—	600	25	B,C	2(105)

8WA2511-1DF300	26-12	Cu	2	—	300	25	B,D	(105),4,#2
8WA2511-1DG20	26-10	Cu	2	—	600	33	C	2(105)
8WA2511-1DG30	26-10	Cu	2	—	600	33	C	2(105)
8WA2511-1PF20	26-12	Cu	2	—	—	—	—	2(105)4,6
8WA2511-1PF30	26-10	Cu	2	—	—	—	—	2(105)4,6
8WA2511-1PG20	26-10	Cu	2	—	—	—	—	2(105)
8WA2511-1PG30	26-10	Cu	2	—	—	—	—	2(105)
8WA3011-1DE20	22-16(1)	Cu	2	—	600	10	B,C,D	2(105),4
8WA3011-1DE30	26-12(2)	Cu	2	—	600	10	B,C,D	2(105),4
8WA3011-1DE40	26-12(2)	Cu	2	—	600	10	B,C,D	2(105),4
8WA3021-1DE20	26-12(2)	Cu	2	—	600	10	B,C,D	2(105),4
8WA3031-1DE20	26-12(2)	Cu	2	—	600	10	B,C,D	2(105),4
8WA3011-1PE20	22-16(1)	Cu	2	—	600	10	B,C,D	2 (105),4,#10
8WA3011-1PE30	26-12(2)	Cu	2	—	600	10	B,C,D	2 (105),4,#10
8WA3011-1PE40	26-12(2)	Cu	2	—	600	10	B,C,D	2 (105),4,#10
8WA3021-1PE20	26-12(2)	Cu	2	—	600	10	B,C,D	2 (105),4,#10
8WA3031-1PE20	26-12(2)	Cu	2	—	600	10	B,C,D	2 (105),4,#10
8WA1012-IDL-14	6-3/0	Cu	2	90	600	200	C	2(105),4#
	6-3/0	Cu	2	90	125, 600, 600	165	A,B,C	2(105),4#
5ST2 511	3/0-350	Cu	2	230	600	310	B,C	2(140),4,2
5ST2 508	2-4(1)	Cu	2	170	600	230	B,C	2(140),4,2
5ST2 504	8-4/(2)/	Cu	2	13.5/	600	80	B,C	2(105),4,2
	8-4			7.2				
	(3)10-14			7.2				
5ST2 505	8-2(Line)	Cu	2	31	600	115	B,C	2(105)
8WH1000-OCN07	1/0-6	Cu	2	70	N/A	N/A	B,C	2(105),4
8WH9120-OBA00	6-24	Cu	2	11-20	600	65	B,C	2(105)
8WH1060-OAL00	6-4	Cu	2	40	600	85	B,C	2(105)
8WH1060-OAN00	6-1/0	Cu	2	70	600	150	B,C	2
8WH1000-OAN00	6-1/0	Cu	2	70	600	150	B,C	2
8WH1000-OAN01	6-1/0	Cu	2	70	600	150	B,C	2
8WH1060-OAQ00	2-4/0	Cu	2	175	600	230	B,C	2(105)
8WH1000-OAQ00	2-4/0	Cu	2	175	600	230	B,C	2(105)
8WH1000-OAQ01	2-4/0	Cu	2	175	600	230	B,C	2(105)
8WH1060-OAS00	2-300	Cu	2	270	600	285	B,C	2(105)
8WH1000-OAS00	2-300	Cu	2	270	600	285	B,C	2(105)
8WH1000-OAS01	2-300	Cu	2	270	600	285	B,C	2(105)
8WH1060-OAU00	500	Cu	2	270	600	380	B,C	2(105)
8WH1000-OAU00	500	Cu	2	270	600	380	B,C	2(105)
8WH9040-1KB00, 8WH9040-1KB01, 8WH9040-1KB07, 8WH9040-1LB00, 8WH9040-1LB01, 8WH9040-1LB07, 8WH9040-1MB00, 8WH9040-1MB01, 8WH9040-1MB07	24-10	Cu	2	N/A	600	30	B,C	2(120),4
8WH2000-OAE00	26-14	Cu	2	N/A	300	15	B,C	2(105)
8WH2000-OCE07	26-14	Cu	2	N/A	—	—	B,C	2(105)
8WH2004-OAE00, 8WH2004-OAE01	26-14	Cu	2	N/A	300	15	B,C	2(105)
8WH2004-OCE07	26-14	Cu	2	N/A	—	—	B,C	2(105)
8WH2003-OAE00, 8WH2003-OAE01	26-14	Cu	2	N/A	300	15	B,C	2(105)

8WH2003-OCE07	26-14	Cu	2	NA	—	—	B,C	2(105)
8WH2000-OAG00	28-10	Cu	2	N/A	600	30	B,C	2(105),4
8WH2000-OAG01	28-10	Cu	2	N/A	600	30	B,C	2(105),4
8WH5100-2KG00	28-10	Cu	2	N/A	600	30	B,C	2(105),4
8WH5100-2KG01	28-10	Cu	2	N/A	600	30	B,C	2(105),4
8WH5100-3KG07	28-10	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH2000-1AG08	24-10	Cu	2	N/A	300	30	B,C	2(105),4
8WH2000-1BG28	24-10	Cu	2	N/A	300	30	B,C	2(105),4
8WH2000-1BG38	24-10	Cu	2	N/A	300	30	B,C	2(105)
8WH2000-1GG08	28-10	Cu	2	N/A	300	6.3	B,C	2(105),4
8WH2000-1HG08	28-10	Cu	2	N/A	300	10	B,C	2(120),4
8WH2000-1MG08	28-10	Cu	2	N/A	300	6.3	B,C	2(105),4
8WH2000-1RG08	28-10	Cu	2	N/A	300	10	B,C	2(120),4
8WH2000-1JG38	28-10	Cu	2	N/A	300	6.3	B,C	2(105),4
8WH2000-1NG38	28-10	Cu	2	N/A	300	10	B,C	2(120),4
8WH2000-1JG68	28-10	Cu	2	N/A	300	6.3	B,C	2(105),4
8WH2000-6CG00,	28-10	Cu	2	N/A	600	30	B,C	2(105),4
8WH2000-OCG07	28-10	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH2040-4LG00	28-10	Cu	2	N/A	(#)	(##)	B,C	2(105),4
8WH2004-OAG00, 8WH2004-OAG01	28-10	Cu	2	N/A	600	30	B,C	2(105),4
8WH2003-OAG00, 8WH2003-OAG01, 8WH2504-OAG00, 8WH2504-OAG01, 8WH2503-OAG00, 8WH2503-OAG01	28-10	Cu	2	N/A	600	30	B,C	2(105),4
8WH2003-OCG07, 8WH2504-OCG07, 8WH2503-OCG07	28-10	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH2500-OAG00, 8WH2500-OAG01	28-10	Cu	2	N/A	600	30	B,C	2(105),4
8WH2500-OCG07	28-10	Cu	2	N/A	—	—	B,C	2(105),4
8WH2020-OAE00, 8WH2020-OAE01, 8WH2020-OCE07	26-14	Cu	2	N/A	300	15	B,C	2(105)
8WH2020-OAG00, 8WH2020-OAG01	28-10	Cu	2	N/A	300	30	B,C	2(105),4
8WH2020-OCG07	20-14	Cu	2	NA	—	—	B,C	2(105),4
8WH2025-OAG00	28-10	Cu	2	N/A	300	30	B,C	2(105),4
8WH9050-OLB00, 8WH9050-OLB01, 8WH9050-OLB07	26-12	Cu	2	N/A	300	20	B,C	2(105),4
8WH2000-OAF00, 8WH2000-OAF01	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH5100-2KF00, 8WH5100-2KF01	28-12	Cu	2	N/A	300/600	20(2)	B,D	2(105)
8WH5100-3KF07	28-12	Cu	2	N/A	300/600	20(2)	B,D	2(105)
8WH5000-OAF00, 8WH5000-OAF01	N/A	Cu	1	N/A	600	20	B,C	2(105)
8WH5000-OCF07	N/A	Cu	1	N/A	N/A	N/A	B,C	2(105)
8WH2000-6CF00	28-12	Cu	2	N/A	600	16	B,C	2(105),4
8WH2000-OCF07	28-12	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH2040-4LF00	28-12	Cu	2	N/A	600	20	B,D	2(105),4
8WH2004-OAF00,	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH2004-OAF01	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH5104-2MF01, 8WH5104-2MF00	28-12	Cu	2	N/A	300/600	20(2)	B,D	2(105)
8WH5104-3MF07	28-12	Cu	2	N/A	300/600	20(2)	B,D	2(105)
8WH5004-OAF00, 8WH5004-OAF01	N/A	Cu	1	N/A	600	20(2)	B,D	2(105)
8WH5004-OCF07	N/A	Cu	1	N/A	N/A	N/A	B,D	2(105)
8WH2004-6CF00, 8WH2004-6CF01	28-12	Cu	2	N/A	600	16	B,C	2(105),4
8WH2004-OCF07	28-12	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH2004-6AF00	28-12	Cu	2	N/A	300	16	B,D	2(105),4

8WH2000-6AF00	28-12	Cu	2	N/A	300	16	B,D	2(105),4
8WH2003-0AF00, 8WH2003-0AF01	28-12	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH5103-2LF00, 8WH5103-2LF01	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH5103-3LF07	28-12	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH2003-5DF00, 8WH2003-5CF00	28-12	Cu	2	N/A	600	20(1)	B,C	2(105)
8WH2003-6CF00	12-26	Cu	2	N/A	600	16	B,C	2(105),4
8WH5103-6EF00	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH2003-0CF07	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH2003-6AF00	28-12	Cu	2	N/A	300	16	B,D	2(105),4
8WH5103-6FF00	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH2500-0AF00, 8WH2500-0AF01	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH2500-6CF00	28-12	Cu	2	N/A	300	16	B,D	2(105),4
8WH2500-0CF07	28-12	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH2504-0AF00, 8WH2504-0AF01	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH2500-6AF00	28-12	Cu	2	N/A	300	16	B,D	2(105),4
8WH2503-0AF00, 8WH2503-0AF01	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH2503-0CF07	28-12	Cu	2	N/A	—	—	B,C	2(105),4
8WH2020-0AF00, 8WH2020-0AF01	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH5120-2MF00, 8WH5120-2MF01	28-12	Cu	2	N/A	300/600	20(2)	B,D	2(105)
8WH5120-3MF07	28-12	Cu	2	N/A	300/600	20(2)	B,D	2(105)
8WH5125-2MF00, 8WH5125-2MF01	28-12	Cu	2	N/A	300/600	20(2)	B,D	2(105)
8WH2020-5EF00	28-12	Cu	2	N/A	600	20(1)	B,C	2(105),4
8WH2020-5FF00	28-12	Cu	2	N/A	600	20(1)	B,C	2(105),4
8WH2020-5HF00, 8WH2020-5GF00	28-12	Cu	2	N/A	600	20(1)	B,C	2(105),4
8WH2020-5AF00	28-12	Cu	2	N/A	600	20(1)	B,C	2(105),4
8WH2020-5DF00	28-12	Cu	2	N/A	600	20(1)	B,C	2(105),4
8WH2020-5BF00	28-12	Cu	2	N/A	600	20(1)	B,C	2(105),4
8WH2020-4CF00	28-12	Cu	2	N/A	300	20	B,D	2(105),4
8WH2020-5JF30, 8WH2020-5JF60	28-12	Cu	2	N/A	600	20	B,C	2(105)
8WH2020-5JF80	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH2020-0CF07	28-12	Cu	2	N/A	N/A	N/A	B,D	2(105),4
8WH2020-4AF00	28-12	Cu	2	N/A	300	20	B,D	2(105),4
8WH2020-4BF00	28-12	Cu	2	N/A	300	20	B,D	2(105),4
8WH2025-0AF00, 8WH2025-0AF01	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH2023-0AF00, 8WH2023-0AF01	28-12	Cu	2	N/A	300	20	B,D	2(105),4
8WH2023-0CF07	28-12	Cu	2	N/A	N/A	N/A	B,D	2(105),4
8WH2022-0AF00	28-12	Cu	2	N/A	300	20	B,D	2(105),4
8WH2520-0AF00, 8WH2520-0AF01	28-12	Cu	2	N/A	300	20	B,D	2(105),4
8WH2520-0CF07	28-12	Cu	2	N/A	N/A	N/A	B,D	2(105),4
8WH2000-0AJ00, 8WH2000-0AJ01	16-6	Cu	2	N/A	600	65	B,C	2(105)
8WH2000-0CJ07	16-6	Cu	2	N/A	—	—	B,C	2(105)
8WH2000-0AK00, 8WH2000-0AK01	16-4	Cu	2	N/A	600	65	B,C	2(105)
8WH2000-0CK07	16-4	Cu	2	N/A	—	—	B,C	2(105)
8WH2000-0AM00, 8WH2000-0AM01	14-2	Cu	N/A	2	600	115	B,C	2(105),4
8WH2000-0CM07	14-2	Cu	N/A	2	N/A	N/A	B,C	2(105),4
8WH2000-0AH00, 8WH2000-0AH01, 8WH2003-0AH00, 8WH2003-0AH01	24-8	Cu	2	N/A	600	50	B,C	2(105),4
8WH2003-0CH07, 8WH2000-0CH07	24-8	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH2500-0AH00, 8WH2500-0AH01, 8WH2503-0AH00, 8WH2503-0AH01	24-8	Cu	2	N/A	600	50	B,C	2(105),4

8WH2500-0CH07, 8WH2503-0CH07	24-8	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH3000-0AE00, 8WH3000-0AE01, 8WH3000-6AE00	24-16	Cu	2	N/A	600	10	B,C	2
8WH3000-0CE07	24-16	Cu	2	N/A	N/A	N/A	B,C	2
8WH3004-0AE00, 8WH3004-0AE01	24-16	Cu	2	N/A	600	10	B,C	(120),4
8WH3004-0CE07	24-16	Cu	2	N/A	N/A	N/A	B,C	(120),4
8WH3003-0AE00, 8WH30003-0AE01	24-16	Cu	2	N/A	600	10	B,C	(120),4
8WH3003-0CE07	24-16	Cu	2	N/A	N/A	N/A	B,C	(120),4
8WH3000-0AF00, 8WH3000-0AF01	20-14	Cu	2	N/A	600	15	B,C	2(105),4
8WH3000-0CF07, 8WH3003-0CF07	20-14	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH3003-0AF00, 8WH3003-0AF01	20-14	Cu	2	N/A	600	15	B,C	2(105),4
8WH3020-0AE00, 8WH3020-0AE01	24-16	Cu	2	N/A	600	10	B,C	2
8WH3020-5AE00	24-16	Cu	2	N/A	600	10	B,C	(120),4
8WH3020-0CE07	24-16	Cu	2	N/A	N/A	N/A	B,C	2(120),4
8WH3100-2GE00, 8WH3100-2GE01	Input 24-26; Output 26-12	Cu	2	N/A	600	10	B,C	2(105),4
8WH3100-3GE07	Input 24-26; Output 28-12	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH3103-2HE00, 8WH3103-2HE01	Input 24-26; Output 26-12	Cu	2	N/A	600	10	B,C	2(105),4
8WH3103-3HE07	Input 24-26; Output 28-12	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH3100-2DE00, 8WH3100-2DE01, 8WH3103-2DE00, 8WH3103-2DE01	Input 24-26; Output 26-12	Cu	2	5-7	600	10	B,C	2(105),4
8WH3100-3DE07, 8WH3103-3DE07	Input 24-26; Output 26-12	Cu	2	5-7	N/A	N/A	B,C	2(105),4
8WH3120-2JE00, 8WH3120-2JE01	Input 24-26; Output 26-12	Cu	2	N/A	300	10	B,C	2(105),4
8WH3120-3JE07	Input 24-26; Output 28-12	Cu	2	N/A	N/A	N/A	B,C	2(105),4
8WH3120-2FE00, 8WH3120-2FE01	Input 24-26; Output 26-12	Cu	2	5-7	300	10	B,C	2(105),4
8WH3120-3FE07	Input 24-26; Output 26-12	Cu	2	5-7	N/A	N/A	B,C	2(105),4
8WH1001-0AK00,	4-22	Cu	2	18-25	600	85	B,C	2(105)
8WH1001-0AM00,	2-18	Cu	2	30-50	600	115 (+)	B,C	2(105),4
8WH1001-0CK07	22-4	Cu	2	18-25	N/A	N/A	B,C	2(105),4
8WH1001-0CM07	2-18	Cu	2	18	NA	NA	B,C	2(105),4
8WH9126-0BA01	6-18	Cu	2	25	300	65	B,C	2(105),4
8WH9127-0BA01	2-18	Cu	2	50	300	115	B,C	2(105),4
8WH2000-0AE04, 8WH2000-0AE02, 8WH2000-0AE08, 8WH2000-0AE03, 8WH2000-0AE05, 8WH2000-0AE06	26-14	Cu	2	N/A	300	15	B,C	2(105)
8WH2000-0AF04, 8WH2000-0AF02, 8WH2000-0AF08, 8WH2000-0AF03, 8WH2000-0AF05, 8WH2000-0AF06	28-12	Cu	2	N/A	600	20	B,C	2(105),4
8WH2000-0AG04, 8WH2000-0AG02, 8WH2000-0AG08, 8WH2000-0AG03, 8WH2000-0AG05, 8WH2000-0AG06	28-10	Cu	2	N/A	600	30	B,C	2(105),4
Note: (+) 130A max for factory-wiring only.								
8WH1020-0CF07	26-12	Cu	2	4-5	N/A	N/A	B,C	2(105),4
	26-10(3)	Cu	2	5-7	600	10	B,C	2(105),4

8WH1000-1GG08, 8WH1000-1KG38, 8WH1000-1MG88								
8WH1000-6CG00	26-10(3)	Cu	2	5-7	600	16	B,C	2(105),4
8WH1000-6LG00, 8WH1000-6KG00	26-10(3)	Cu	2	5-7	600	0.5	B,C	2(105),4
8WH1000-1PH38, 8WH1000-1HH08	24-8	Cu	2	13-15	600	10 (5)	B,C	2(105),
8WH1020-5FF00	26-12	Cu	2	4-5	300, 600	20 (8), 5	B,D	2(105),4
8WH1020-5HF00	26-12	Cu	2	4-5	300, 600	20, 5	B,D	2(105),4
8WH1020-5DF00	26-12	Cu	2	4-5	300, 600	20 (8), 5	B,D	2(105),4
8WH1020-5AF00, 8WH1020-5BF00	26-12	Cu	2	4-5	300, 600	20, 5	B,D	2(105),4
8WH1000-7BH00	26-8	Cu	2	12-13	600	30	B,C	2(105),4
8WH1000-7AH00	26-8	Cu	2	12-13	600	30	B,C	2(105),4
5ST2 507	Input - No. 8-2/0; Output - 6 No. 14-4	Cu	2	Input - 35.5; Output - 17.5	600	160	B,C	2(140),4
8WH6003-ODE00	26-14	Cu	2	N/A	300	15	B	2(105), 4
					150	15	C	
					300	10	D	
8WH6003-OFE00	26-14	Cu	2	N/A	300	15	B	2(105), 4
					150	15	C	
					300	10	D	
8WH6003-OHE00	26-14	Cu	2	N/A	N/A	N/A	B, C, D	2(105), 4
8WH6004-ODE00	26-14	Cu	2	N/A	300	15	B	2(105), 4
					150	15	C	
					300	10	D	
8WH6004-OFE00	26-14	Cu	2	N/A	300	15	B	2(105), 4
					150	15	C	
					300	10	D	
8WH6004-OHE00	26-14	Cu	2	N/A	N/A	N/A	B, C, D	2(105), 4
8WH6004-OHE04	24-12	Cu	2	N/A	N/A	N/A	B, C, D	2(105), 4
8WH6004-OHE04	26-8	Cu	2	12-13	600	30	B, C	2(105), 4
8 WH1 000-7BH00	26-8	Cu	2	12-13	600	30	B, C	2(105), 4
8WH6000-0AM00, 8WH6000-0AM01	14-2	Cu	2	N/A	1000	115	E	2(120), 4
8WH6000-0CM07	14-2	Cu	2	N/A	1000	—	E	2(120), 4
8WH6000-1GG08	24-10 str/sol	Cu	2	N/A	300	6.3	B, C	2(105), 4
8WH6000-1MG88	24-10 str/sol	Cu	2	N/A	250	6.3	B, C	2(105), 4
8WH6000-1KG38	24-10 str/sol	Cu	2	N/A	30	6.3	B, C	2(105), 4
8WH10010AM01	2-18	Cu	2	30-50	600	115 (+)	B, C	2(105), 4
8WH10010AK01	4-22	Cu	2	13-16	600	85	B, C	2(105), 4
8WH25200AG00	28-10	Cu	2	N/A	300	30	B, C	2(105), 4
8WH1000-1RH88	24-8	Cu	2	13-15	600	10(5)	B, C	2(105), 4
8WH1000-1QH68	24-8	Cu	2	13-15	600	10(5)	B, C	2(105), 4
8WH10000AH00	24-8(4)	Cu	2	13-15	600	50	B, C	2(105), 4
8WH10000AG00	26-10(3)	Cu	2	5-7	600	30(1)	B, C	2(105), 4
8WH9120-0DA00		Cu	2	—	1000	57	E	2(120), 4



	20 (sol/str) -6								
8WH10006AH00	24-8(4)	Cu	2	13-15	300	16	B, C	2(105), 4	
8WH10006AH00	24-8(4)	Cu	2	13-15	600	5	D	2(105), 4	
8WH10206AG00	26-10(3)	Cu	2	5-7	300	30(6)	B, C	2(105), 4	
8WH10206AG00	26-10(3)	Cu	2	5-7	600	5	D	2(105), 4	
8WH10206AC00	26-10(3)	Cu	2	5-7	300	30(6)	B, C	2(105), 4	
8WH10206AC00	26-10(3)	Cu	2	5-7	600	5	D	2(105), 4	

Cat. No.	Line	Suitable Conductors kcmil/AWG	Load	OverCurrent Protection Fuse Required Class/Max Amp Rating						SCCR, RMS Sym, kA	Volts Max
				J	T	RK1	RK5	G	CC		
5ST2 504	8-4	14-10 sol/str		80	—	—	—	—	—	100,000	600
5ST2 504	4	4		—	—	—	100	—	—	100,000	600
5ST2 504	14	14 sol/str		—	—	—	30	—	—	100,000	600
5ST2 505	8-2	14-4 sol/str		125	—	—	—	—	—	100,000	600
5ST2 505	2	(1)No. 4 AWG + (1)No. 10 AWG sol/str		—	—	—	100	—	—	100,000	600
5ST2 505	8	14 sol/str		—	—	—	30	—	—	100,000	600
5ST2 507	8-2/0	14-4 sol/str		175	—	—	—	—	—	100,000	600
5ST2 507	2/0	(2) No. 4 AWG		—	—	—	100	—	—	100,000	600
5ST2 507	8	14 sol/str		—	—	—	30	—	—	100,000	600
5ST2 508	2-4/0	14-6 AWG (Top), 14-8 AWG (Mid), 14-2 AWG (Bottom)		250	—	—	—	—	—	100,000	600
5ST2 508	4/0	(2) No. 2 AWG bottom		—	—	—	100	—	—	100,000	600
5ST2 508	2	14 AWG Sol/STR (Bottom)		—	—	—	30	—	—	100,000	600
5ST2 511	3/0 - 350	14-6 AWG (Top), 14-8 AWG (Mid), 14-2 AWG (Bottom)		350	—	—	—	—	—	100,000	600
5ST2 511	350 kcmil	(2) No. 2 AWG + (1) No. 8 AWG + (1) No. 10 AWG bottom		—	—	—	100	—	—	100,000	600
5ST2 511	3/0	14 AWG Sol/Str (Bottom)		—	—	—	30	—	—	100,000	600
8WH10000CQ07	2-4/0 Cu	2-4/0 Cu		200	200	200	60	60	30	100	N/A
8WH91200CA00	2-300 kcmil Cu	2-300 kcmil Cu		200	200	100	30	60	30	100	600
8WH91200CA00	2-300 kcmil	2-300 kcmil Cu		400	400	200	100	60	30	100	600
8WH91200CA00	2/0-500 kcmil Cu	2/0-500 kcmil Cu		200	200	100	30	60	30	100	600
8WH91200CA00	2/0-500 kcmil	2/0-500 kcmil Cu		400	400	200	100	60	30	100	600
8WH91200AA00	6-1/0 Cu	6-1/0 Cu		200	200	100	30	60	30	100	600
8WH2 003-0AG05	14-10 Cu	14-10 Cu		60	60	—	—	30	30	100	600
8WH20006AG00	14-10 Cu	14-10 Cu		60	60	—	—	30	30	100	300
8WH2 003-0AG08 8WH2 003-0AG03 8WH2 003-0AG02 8WH2 003-0AG06 8WH2 003-0AG04, 8WH1000-6HG08	14-10 Cu	14-10 Cu		60	60	—	—	30	30	100	600
8WH2 003-0AE08 8WH2 003-0AE03 8WH2 003-0AE02 8WH2 003-0AE06 8WH2 003-0AE04	14 Cu	14 Cu		60	60	—	—	30	30	100	300
8WH20250AE00	14 Cu	14 Cu		60	60	—	—	30	30	100	300
8WH20030AE00 8WH20030AE01 8WH2 003-0AE05	14 Cu	14 Cu		60	60	—	—	30	30	100	300
8WH2003-0AF05	14-12 Cu	14-12 Cu		60	60	—	—	30	30	100	600

8WH20350CF07	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100	N/A
8WH20304HF00 8WH20304EF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100	N/A
8WH20350AF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100	300
8WH20300AF01 8WH20300AF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100	300
8WH10250AF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100	300
8WH10000CG07, 8WH1000-6JG07	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100	N/A
8WH31002DF00	14 Cu	14 Cu	60	60	—	—	30	30	100	600

(1) 25A max. for factory wiring only.

#In CA column indicates a unique condition of acceptability and are indicated in individual Component Recognition Reports.

#10 The suitability of fuses used with this device shall be judged in the end-use.

Cat. No.	Suitable Conductors kcmil/AWG		OverCurrent Protection Fuse Required Class/Max Amp Rating							SCCR, RMS Sym, kA	Volts Max
	Line	Load	J	T	RK1	RK5	G	CC			
8WH3000-0AF00	14 Cu	14 Cu	60	60	—	—	30	30	100,000	600	
8WH3000-0CF07	14 Cu	14 Cu	60	60	—	—	30	30	100,000	N/A	
8WH3003-0AF00	14 Cu	14 Cu	60	60	—	—	30	30	100,000	600	
8WH3003-0CF07	14 Cu	14 Cu	60	60	—	—	30	30	100,000	N/A	
8WH2000-0AE00	14 Cu	14 Cu	60	60	—	—	30	30	100,000	300	
8WH2000-0CE07	14 Cu	14 Cu	60	60	—	—	30	30	100,000	N/A	
8WH2004-0AE00	14 Cu	14 Cu	60	60	—	—	30	30	100,000	300	
8WH2004-0CE07	14 Cu	14 Cu	60	60	—	—	30	30	100,000	N/A	
8WH2003-0AE00	14 Cu	14 Cu	60	60	—	—	30	30	100,000	300	
8WH2003-0CE07	14 Cu	14 Cu	60	60	—	—	30	30	100,000	N/A	
8WH2020-0AE00	14 Cu	14 Cu	60	60	—	—	30	30	100,000	300	
8WH2020-0CE07	14 Cu	14 Cu	60	60	—	—	30	30	100,000	N/A	
8WH2000-6CF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	600	
8WH2004-6CF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	600	
8WH2004-6AF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	300	
8WH2000-6AF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	300	
8WH2003-6CF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	600	
8WH2003-6AF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	300	
8WH2000-0AF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	600	
8WH2000-0CF07	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	N/A	
8WH2504-0AF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	600	
8WH2504-0CF07	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	N/A	
8WH2003-0AF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	600	
8WH2003-0CF07	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	N/A	
8WH2020-0AF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	600	
8WH2000-0AG00	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	600	
8WH2000-0CG07	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	N/A	
8WH2003-0AG00	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	600	
8WH2003-0CG07	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	N/A	
8WH2004-0AG00	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	600	
8WH2004-0CG07	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	N/A	
8WH2020-0AG00	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	300	
8WH2025-0AG00	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	300	

8WH2020-0CG07	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	N/A
8WH2000-6CG00	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	300
8WH2000-0AH00	14-8 Cu	14-8 Cu	100	100	30	30	60	30	100,000	600
8WH2000-0CH07	14-8 Cu	14-8 Cu	100	100	30	30	60	30	100,000	N/A
8WH1000-0CH07	14-8 Cu	14-8 Cu	100	100	30	30	60	30	100	N/A
8WH2000-0AK00	14-4 Cu	14-4 Cu	100	100	30	30	60	30	100,000	600
8WH2000-0CK07	14-4 Cu	14-4 Cu	100	100	30	30	60	30	100,000	N/A
8WH2000-0AM00	14-2 Cu	14-2 Cu	200	200	100	30	60	30	100,000	600
8WH2000-0CM07	14-2 Cu	14-2 Cu	200	200	100	30	60	30	100,000	N/A
8WH1000-0AK00, 8WH1000-0AK01	14-4 Cu	14-4 Cu	100	100	30	30	60	30	100,000	600
8WH1000-0CK07	14-4 Cu	14-4 Cu	100	100	30	30	60	30	100,000	N/A
8WH1000-0AM00, 8WH1000-0AM01	14-1/0 Cu	14-1/0 Cu	200	200	100	30	60	30	100,000	600
8WH1000-0CM07	14-1/0 Cu	14-1/0 Cu	200	200	100	30	60	30	100,000	N/A
8WH1020-0AF00, 8WH1020-0AF01	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100,000	300
8WH1025-0AG00	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	300
8WH1020-0CG07	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	N/A
8WH1020-0AG00	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	300
8WH1000-6CG00	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	600
8WH1000-6AG00	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100,000	600

Cat. No.	Suitable Conductors kcmil/AWG		OverCurrent Protection Fuse Required Class/Max Amp Rating						SCCR, RMS Sym, kA	Volts Max
	Line	Load	J	T	RK1	RK5	G	CC		
8WH1000-0CN07	6-1/0 Cu	6-1/0 Cu	100	100	60	30	60	30	100	N/A
8WH1000-0AN00	6-1/0 Cu	6-1/0 Cu	100	100	60	30	60	30	100	600
8WH1000-0AQ00	2-4/0 Cu	2-4/0 Cu	200	200	200	60	60	30	100	600
8WH1000-0AS00	2-300 kcmil Cu	2-300 kcmil Cu	200	200	200	60	60	30	100	600
8WH1000-0AU00	2/0-500 kcmil Cu	2/0-500 kcmil Cu	200	200	200	60	60	30	100	600
8WH2000-0AE01	14 Cu	14 Cu	60	60	—	—	30	30	100	N/A
8WH2040-4LF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100	300
8WH2004-0AF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100	600
8WH2004-0CF07	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100	N/A
8WH2000-0AE04, 8WH2000-0AE02, 8WH2000-0AE08, 8WH2000-0AE03, 8WH2000-0AE05, 8WH2000-0AE06	14 Cu	14 Cu	60	60	—	—	30	30	100	300
8WH2000-0AF04, 8WH2000-0AF02, 8WH2000-0AF08, 8WH2000-0AF03, 8WH2000-0AF05, 8WH2000-0AF06	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100	600
8WH2000-0AG04, 8WH2000-0AG02, 8WH2000-0AG08, 8WH2000-0AG03, 8WH2000-0AG05, 8WH2000-0AG06, 8WH1000-6GG00	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100	600
8WH1000-0AF04, 8WH1000-0AF06, 8WH1000-0AF02, 8WH1000-0AF08, 8WH1000-0AF03	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100	600
8WH1000-0AG04, 8WH1000-0AG02, 8WH1000-0AG08	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100	600
8WH1000-0AH02, 8WH1000-0AH08	14-8 Cu	14-8 Cu	100	100	30	30	60	30	100	600
8WH2103-2BG00, 8WH2103-2BG01, 8WH2103-3BG07	14-10 Cu	14-10 Cu	60	60	—	—	30	30	100	600
8WH2035-0AF01, 8WH1025-0AF00	14-12 Cu	14-12 Cu	60	60	—	—	30	30	100	300

Cat. No.	Wire Size	Wire Type	FW	TQ Lb In.	V	A	UG	CA
----------	--------------	--------------	----	-----------------	---	---	----	----

8WH6000-OAF00, 8WH6000-OAF01	24-12 sol/str	Cu	2	N/A	600	20	B,C	2 (105),4
8WH6000-OCF07	24-12 sol/str	Cu	2	N/A	N/A	N/A	B,C	2 (105),4
8WH6003-OAF00, 8WH6003-OAF01	24-12 sol/str	Cu	2	N/A	600	20	B,C	2 (105),4
8WH6003-OCF07	24-12 sol/str	Cu	2	N/A	N/A	N/A	B,C	2 (105),4
8WH5100-2PF00	26-12 str/sol	Cu	2	N/A	300	20	B,C	2(105
8WH5100-3PF07	26-12 str/sol	Cu	2	N/A	N/A	N/A	B,C	2(105
8WH6003-OAG00	24-10 str/sol	Cu	2	N/A	600	30	B,C	2(105)
8WH9125-OAC00	26-10	Cu	2	5-7	600	30	B,C	2 (105),4
8WH9126-OCA00	26-10	Cu	2	5-7	600	30	B,C	2 (105),4
8WH9127-OCA00	26-10	Cu	2	5-7	600	30	B,C	2 (105),4
8WH9050-OAB01	28-10	Cu	2	N/A	600	30	B,C	2 (105),4
8WH9050-OAB07	28-10	Cu	2	N/A	600	30	B,C	2 (105),4
8WH9040-1AB01	28-12	Cu	2	N/A	300/600	20 (2)	B,D	2(105)
8WH9040-1AB07	28-12	Cu	2	N/A	300/600	20 (2)	B,D	2(105)
8WH9040-1AB00	28-12	Cu	2	N/A	300/600	20 (2)	B,D	2(105)
8WH1000-OAJ00, 8WH1000-OAJ01	20-6	Cu	2	13-15	600	65	B,C	2 (105),4
8WH1000-OCJ07	20-6	Cu	2	13-15	N/A	N/A	B,C,D	2 (105),4
8WH1000-OAF00, 8WH1000-OAF01	26-12 (2)	Cu	2	4-5	600	20	B,C	2 (105),4
8WH1000-OCF07	26-12 (2)	Cu	2	4-510	N/A	N/A	B,C,D	2 (105),4
8WH1000-OAG01	26-10 (3)	Cu	2	5-7	600	30 (1)	B,C	2 (105),4
8WH1000-OAH01	24-8(4)	Cu	2	13-15	600	50	B,C	2 (105),4
8WH100-OCH07	24-8(4)	Cu	2	13-15	N/A	N/A	B,C,D	2 (105),4
8WH1020-OAG00, 8WH1020-OAG01	14-10 Cu	14-10 Cu	60	60	—	—	30	30
8WH6020-OCF07	26-12 sol/str	Cu	2	N/A	N/A	N/A	B,C,D	2 (105),4
8WH6025-OAF00	26-12 sol/str	Cu	2	N/A	300	20	B,C	2 (105),4
					600	5	D	
8WH6020-OAF00, 8WH6020-OAF01	26-12 sol/str	Cu	2	N/A	300	20	B,C	2 (105),4
					600	5	D	
8WH6020-OAG00, 8WH6020-OAG01	24-10 str/sol	Cu	2	N/A	300	28	B,C	2(105)4
	24-10 str/sol	Cu	2	N/A	600	5	D	2(105)
8WH6025-OAG00	24-10 str/sol	Cu	2	N/A	300	30	B,C	2(105)4
	24-10 str/sol	Cu	2	N/A	600	5	D	2(105)4
8WH6020-OCG07	24-10 str/sol	Cu	2	N/A	N/A	N/A	B,C,D	2(105)4

8WH1020-5JF30, 8WH1020-5LF00	26-12 (2)	Cu	2	4-5	300	20	B,C	2 (105),4
		Cu	2	4-5	600	5	D	2 (105),4
8WH6000-6AG00	24-10 str/sol	Cu	2	N/A	300	20	B,C	2(105)4
8WH6000-6CG00	24-10 str/sol	Cu	2	N/A	600	20	B,C	2(105)4
8WH6000-6AF00	26-12 str/sol	Cu	2	N/A	300	20	B,C	2(105)
	26-12 str 26-12 sol	Cu	2	N/A	300	20 16	B,C	2(105)
8WH6003-6AF00	26-12 sol/str	Cu	2	N/A	600	20	B,C	2(105),
8WH6004-6AF00	26-12 sol/str	Cu	2	N/A	600	20	B,C	2 (105),4
8WH6000-6CF00	26-12 str/sol	Cu	2	N/A	300	20	B,C	2(105)
	26-12 str/sol	Cu	2	N/A	300	10	B,C	2(105)
8WH6003-6CF00	26-12 str 26-12 sol	Cu	2	N/A	300	20 16	B,C	2(105)
	26-12 str/sol	Cu	2	N/A	300	10	B,C	2(105)
8WH6004-6CF00	26-12 str/sol	Cu	2	N/A	300	20 16	B,C	2(105)
	26-12 str/sol	Cu	2	N/A	300	10	B,C	2(105)
8WH2004-0AF04, 8WH2004-0AF02, 8WH2004-0AF03, 8WH2004-0AF06, 8WH2004-0AF08	28-12	Cu	2	N/A	600	20	B,C	2 (105),4
8WH2003-0AF04, 8WH2003-0AF02, 8WH2003-0AF03, 8WH2003-0AF06, 8WH2003-0AF08	28-12	Cu	2	N/A	600	20	B,C	2 (105),4
8WH1020-5JF30	26-12 (2)	Cu	2	4-5	300	20	B,C	2 (105),4
8WH2103-2BF00, 8WH2103-2BF01, 8WH2103-3BF07	28-12	Cu	2	N/A	600	20	B,C	2 (105),4
8WH2103-2BG00, 8WH2103-2BG01	28-10	Cu	2	N/A	600	30	B,C	2 (105),4
8WH2103-3BG07	28-10	Cu	2	N/A	N/A	N/A	B,C	2 (105),4
8WH6000-0AK00, 8WH6000-0AK01	20-4 str/sol	Cu	2	N/A	600	85	B,C	2(105)
8WH6000-0CK07	20-4 str/sol	Cu	2	N/A	600	N/A	B,C	2(105)
8WH6000-0AN00, 8WH6000-0AN01	8-1/0	Cu	2	—	1000	140	E	2(120), 4
8WH6000-0CN07	8-1/0	Cu	2	—	1000	N/A	E	2(120), 4
8WH6000-0AQ00, 8WH6000-0AQ01	4-4/0	Cu	2	—	1000	230	E	2(120), 4
8WH6000-0CQ07	4-4/0	Cu	2	—	1000	—	E	2(120), 4
8WH6000-0AS00, 8WH6000-0AS01	2-300 kcmil	Cu	2	—	1000	270	E	2(120), 4
8WH6003-0DF04	26-14	Cu	2	N/A	N/A	N/A	B, C, D	2(105), 4
8WH1020-4CF00	26-12 (2)	Cu	2	4-5	300	20	B, C	2(105), 4
		Cu	2	4-5	600	5	D	2(105), 4
8WH9040-1DB00, 8WH9040-1DB01, 8WH9040-1DB07, 8WH9040-1EB00, 8WH9040-1EB01, 8WH9040-1EB07, 8WH9040-1FB00, 8WH9040-1FB01, 8WH9040-1FB07	28-12	Cu	2	N/A	300/600	20 (2)	B, D	2(105)

8WH9040-1BB00, 8WH9040-1BB01, 8WH9040-1CB00, 8WH9040-1CB01, 8WH9040-1CB07	28-12	Cu	2	N/A	300/600	20 (2)	B, D	2(105)
8WH2020-5KF00	28-12	Cu	2	N/A	600	20 (1)	B, C	2(105), 4

Cat. No.	Suitable Conductors Kcmil/AWG		OverCurrent Protection Fuse Required Class/Max Amp Rating							SCCR RMS Sym A	Max Volts
	Line	Load	J	L	T	RK1	RK5	G	CC		
8WH6000-0AJ00, 8WH6000-0AJ01, 8WH6000-0CJ07	14 -6 Str.	14 - 6 Str.	60	—	—	—	—	30	30	100 kA	480 v
8WH6000-0AH01, 8WH6000-0AH00, 8WH6000-0CH07	14 -8 Str.	14 - 8 Str.	60	—	—	—	—	30	30	100 kA	480 ac 3 ph
8WH6000-0CG07, 8WH6000-0AG00, 8WH6000-0AG01, 8WH6003-0AG01, 8WH6003-0CG07, 8WH6004-0AG00, 8WH6004-0AG01, 8WH6004-0CG07	14 -10 Str.	14 - 10 Str.	35	—	—	—	—	30	30	100 kA	480 ac 3 ph
8WH60040AF00, 8WH60040CF07, 8WH6001-0AF00, 8WH6001-4QF00, 8WH6001-4DF00, 8WH6001-4CF00, 8WH6001-0CF07, 8WH6001-4HF00, 8WH6001-4PF00, 8WH6001-4NF00, 8WH6001-4EF00, 8WH6001-4FF00, 8WH6001-4GF00, 8WH6001-4MF00, 8WH6001-0BF01	14 - 12 Str.	14 - 12 Str.	35	—	—	—	—	30	30	100 kA	300 ac 3 ph

Marking: Company name and catalog designation.

Last Updated on 2018-05-17

[Questions?](#)

[Print this page](#)

[Terms of Use](#)

[Page Top](#)

© 2018 UL LLC

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2018 UL LLC".